

1. Start out by lightly oiling the entire CHAIN. The machine has been properly lubricated before leaving the Mereen-Johnson assembly floor. Do not regrease motor bearings.
2. Set up a lubrication schedule. (See the schedule included in the manual.)

Every 400 hours of running time oil the machine. Keep chain clean.

It is recommended that these OILS or their equivalent be used on the Mereen-Johnson Machine Company Equipment.

Ambient Air Temperature +5°F to +77°F. Gulf Oil
CompanyGulf EP S60
Chevron Oil Company .. Non-Leaded Gear Compound 150
American Oil Company Spartan EP 150
Mobil Oil Company Mobilgear 629
Shell Oil Company Omala Oil 100
Texaco Oil Company Meropa 150

Ambient Air Temperature +32°F to +104°F.
Gulf Oil CompanyGulf EP S100
Chevron Oil Company .. Non-Leaded Gear Compound 220
American Oil Company Spartan EP 220
Mobil Oil Company Mobilgear 630
Shell Oil Company Omala Oil 220
Texaco Oil Company Meropa 220

